

4-CYCLE GAS-POWERED INVERTERS AND GENERATORS



Parallelable operation allows for connecting two Pioneer inverters to increase power



Ultra-lightweight design for easy handling

Rear wheel kit with telescoping handle for easy transport



5 HRS

RUN TIME AT
50% LOAD
GASOLINE

20 HRS

RUN TIME AT
50% LOAD
PROPANE



Patent-pending technology shuts down your generator when harmful levels of carbon monoxide are detected.



DUAL-FUEL POWERED 2600-WATT INVERTER

MODEL NO. P2600iDC

The Pioneer 2600-Watt Dual Fuel Inverter Generator provides reliable, portable power for outdoor activities and light home backup power needs. Capable of running on gasoline or propane this unit automatically switches fuel intake between gasoline and propane to extend runtime while delivering clean, stable energy making it ideal for camping, tailgating, or emergency home use.

INCLUDES Oil, Funnel, Tool Kit, Parallel Cable, 30A RV adapter; Propane Regulator; DC battery charging cable, Manual, Quick-Start Guide

SPECIFICATIONS

Engine Type	4-Cycle Dual Fuel Gasoline and Propane-Powered	Starting Watts (Gasoline)	2600	Weight	40 lbs.
Engine Displacement	80cc	Running Watts (Gasoline)	2000	Parallelable	Yes
Starting System	Recoil	Starting Watts (Propane)	2300	Compliance	CSA Approved
Fuel Capacity	3.4 litres	Running Watts (Propane)	1800	Outlets	(2) 120V AC 20A (1) 120V AC 30A (1) 5V, 3.6A, USB-A (1) 5V, 3.0A, USB-C (1) 12V, 8.3A, DC Automotive (1) 30 AMP RV (adaptor included)
LP Cylinder	20 lbs.	Run Time at 50% Load - Gasoline	5 hours		
		Run Time at 50% Load - Propane	20 hours		

