

# 4-CYCLE GAS-POWERED INVERTERS AND GENERATORS



Ultra-lightweight design for easy handling

Rear wheel kit with telescoping handle for easy transport

Fuel Sense Technology automatically selects the fuel type for maximum efficiency



Patent-pending technology shuts down your generator when harmful levels of carbon monoxide are detected.



**7 1/2**  
HRS

RUN TIME AT  
50% LOAD  
GASOLINE

**8 1/2**  
HRS

RUN TIME AT  
50% LOAD  
PROPANE



COMPATIBLE WITH

▶ **240V Parallel and Series Kit**

MODEL NO. PPKS12000

(Parallel Kit Sold Separately)



## DUAL-FUEL POWERED 7600-WATT INVERTER

MODEL NO. P7600iRDC

The Pioneer 7600-Watt Dual Fuel Inverter Generator offers exceptional versatility and reliable performance, ideal for activities requiring heavy power use. Capable of running on gasoline or propane, this unit automatically switches fuel intake between gasoline and propane to extend its runtime while delivering power to larger appliances, tools, RVs, and sensitive electronics. With the convenience of user-friendly controls and remote starting, long run times, and a durable yet portable design, this generator is a perfect home power backup solution.

**INCLUDES** Oil, Funnel, Tool Kit, 30A RV adapter, Propane Regulator, Remote fob, Manual, Quick Start Guide

### SPECIFICATIONS

Engine Type	4-Cycle Dual Fuel Gasoline and Propane-Powered	Starting Watts (Gasoline)	7600	Weight	137 lbs.
Engine Displacement	322cc	Running Watts (Gasoline)	6100	Parallelable	Yes
Starting System	Remote Electric, Recoil	Starting Watts (Propane)	6900	Compliance	CSA Approved
Fuel Capacity	13.6 litres	Running Watts (Propane)	5500	Outlets	(2) 120V AC 20A GFCI (1) 120V AC 30A (1) 120/240V AC 30A (1) 5V, 3.6A, USB-A (1) 5V, 3.0A, USB-C (1) 30 AMP RV (adaptor included)
LP Cylinder	20 lbs.	Run Time at 50% Load - Gasoline	7.5 hours		
		Run Time at 50% Load - Propane	8.5 hours		

