



PORTABLE GENERATOR PRODUCT ASSORTMENT

	30767	30805	30766	030792	030793	030794	30750	033017
DESCRIPTION	B&S INVERTER • P2400	B&S INVERTER • P4500	B&S INVERTER • Q6500	OREGON • 3500W GEN	OREGON • 5500W GEN	OREGON • 6500W GEN	B&S GEN • 8000W ELITE SERIES	B&S GEN • 9200W ELITE SERIES
Running Watts	1800	3700	5000	500	5500	6500	8000	9200
Starting Watts	2400	4500	6500	5250	7000	8200	10000	12000
Engine	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV	Briggs & Stratton OHV
CO Shutdown	Yes	Yes	Yes	Yes	Yes	Yes	YES	YES
Displacement (cc)	79	224	306	196	389	389	420	460
Starting	Recoil	Electric/Recoil with Remote	Recoil	Recoil	Recoil	Key Electric Start / Recoil	Electric/Recoil	Electric/Recoil
Fuel Tank Capacity	1 Gallon	3.4 Gallon	5 Gallon	3 Gallons	5 Gallons	7 Gallons	7.5 Gallons	7.5 Gallons
Run Time (Hours)	8 (25% load)	16 (25% load)	14 (25% load)	8 (50% load)	7 (50% load)	9 (50% load)	9 (50% load)	9 (50% load)
Hour Meter		Yes	-				Yes	Yes
Low Oil Shutdown	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Wheels	No	6 inch	8 inch				12 inch	12 inch
Outlets								
120V, Household	2	4	4	4	4	4	4	4
120V, 30A Locking				-	1	1	-	-
USB	2	2	2	-	-	-	-	-
120V/240V, 20A Locking		-	-	-	-	-	-	-
120V/240V, 30A Locking		-	1	-	-	-	1	1
120 V-30A RV		1	-	1	-	-	-	-
Warranty	3 Year Limited	3 Year Limited	2 Year Limited	2 Year Limited	2 Year Limited	2 Year Limited	3 Year Limited	3 Year Limited



8000 Watt Elite Series™ Portable Generator Model 30750

Equipped with InfoHub™ Portable Power, monitor vital information from the comfort of your home or office. For added protection, CO Guard® carbon monoxide shutdown technology shuts down the generator if harmful levels of CO accumulate in the generator's operating area

SPECIFICATIONS

- 8000 running watts / 10000 starting watts
- CO Guard™ Technology
 - Shuts down your generator when harmful levels of carbon monoxide are detected
- Briggs & Stratton OHV Engine, 420cc
- Multi-featured control panel
 - (2) 120V-20A GFCI duplex outlets
 - (1) 120/240V-30A twist lock outlet
 - Hour meter & protective outlet covers
- 7.5 gallon metal fuel tank with fuel gauge
 - Provides up to 9 hours runtime at 50% load
- Power Surge™ alternator
 - Produces the power needed to start and keep appliances and tools running simultaneously
- 12" Never-Go-Flat wheels
- 3 year limited warranty



9200/12000 Watt Elite Series™ Portable Generator Model 033017

SPECIFICATIONS

- 9200 running watts / 12000 starting watts
- CO Guard™ Technology
 - Shuts down your generator when harmful levels of carbon monoxide are detected
- Briggs & Stratton OHV Engine, 420cc
- Multi-featured control panel
 - (2) 120V-20A GFCI duplex outlets
 - (1) 120/240V-30A twist lock outlet
 - Hour meter & protective outlet covers
- 7.5 gallon metal fuel tank with fuel gauge
 - Provides up to 8 hours runtime at 50% load
- Power Surge™ alternator
 - Produces the power needed to start and keep appliances and tools running simultaneously
- 12" Never-Go-Flat wheels
- 3 year limited warranty